



External IR Dome Camera

These cameras produce great quality images at a budget price. The cameras are housed in an attractive white, silver or grey housing and are fitted with a 3.6mm fixed Megapixel lens providing 700 TVL resolution. The cameras have up the Co-ax control for configuring the menus. The cameras are especially suitable for outside residential properties, small businesses, industrial units and retail outlets.

Mounting The Camera

The camera is for outdoor mounting on a wall or under a lintel.

Powering The Camera

The dome requires a 12V DC regulated power supply and has a standard 2.1mm DC socket for connecting the power. It is recommended to use a power supply that is rated higher than the current consumption of the camera i.e. the current consumption is 275mA add approximately 50% so use a power supply of 500mA or above.

Connecting The Camera To Control Equipment

The dome camera comes with a fly lead for power and video out. To reduce installation time the video out lead is terminated into a female BNC socket connector. This allows the installer to effortlessly connect the camera to control equipment via a male BNC-BNC lead. Remember that the Video out from the camera is like any other electrical circuit and requires two wires to complete the circuit. When using a co-ax type cable such as RG59 or similar, the outer braid of the co-ax provides the "0V GROUND" connection and the inner core provides the "Video" connection.

Accessing The Camera's Menu

The camera's menu system can be accessed and controlled in two ways. The first method is using the in-line joystick on the camera's video lead. The second method is to use an up the Co-ax controller which can be done whilst next to the DVR.

For more information on menu options and what they do see online tip 295 ▶▶▶



Features

- Vandalproof Dome with 24 IR LEDs
- 700TVL
- 1/3" Sony Effio-E
- 3.6mm Megapixel board lens
- Up the Co-ax OSD control

Specification

FUNCTION	SPECIFICATION
CCD	1/3" Sony Effio-E
Resolution	700TVL - 752(H) x 582(V)
Lens	3.6mm Board /F2.0
IRs	24 x IRs up to 20m range
IR Power On	CDS auto control
Video Output	1v p ~ p, 75Ω
Video Connection	BNC
Power/Current	12vDC (± 10%) 275mA
Power Connection	2.1mm DC Socket
Auto Shutter	PAL: 1/50s ~ 1/100,00s
S/N Ratio	More than 48dB
Weatherproof	IP66
Operating Temp.	-10°C ~ +50°C
Dimensions	94mm(D) x 69mm(H)
Weight	400gms

Options Available

PART CODE	DESCRIPTION
CAM080UG	700TVL Eyeball, Grey
CAM080US	700TVL Eyeball, Silver
CAM080UW	700TVL Eyeball, White

Other Products To Consider



2.8-12mm Varifocal 700TVL IR Dome Camera With WDR & UTC. Available In Grey, Silver & White
CAM083U



Up The Co-ax In-line Controller
REM088

All specifications are approximate. System Q Ltd reserves the right to change any product specifications or features without notice. Whilst every effort is made to ensure that these instructions are complete and accurate, System Q Ltd cannot be held responsible in any way for any losses, no matter how they arise, from errors or omissions in these instructions, or the performance or non-performance of the equipment that these instructions refer to.

This symbol on the products and/or accompanying documents means that used electronic equipment must not be mixed with general household waste. For treatment, recovery and recycling please return this unit to your trade supplier or local designated collection point as defined by your local council.
WEE/CG0783SS

Up The Co-ax Menu Control

Up the Co-ax otherwise known as UTC is a method of controlling the cameras OSD using the Co-ax cable. This is achieved using a REM088 in-line controller. The big benefit of configuring a camera via UTC is that it can be done next to the DVR and monitor. The Co-ax cable carrying the camera's video is simply connected to the controller which is then connected to the DVR. Once the camera has been setup, the controller can be removed and the camera is then connected to the DVR as normal.

Menu Page 1

Menu Item	Options
LENS	AUTO / MANUAL AUTO: 1. TYPE: DC / VIDEO 3. SPEED: 0 - 255 2. MODE: AUTO / OPEN / CLOSE
SHUTTER/AGC	AUTO / MANUAL AUTO: HIGH LUMINANCE 1. MODE: SHUT+AUTO IRIS / AUTO IRIS 2. BRIGHTNESS: 0 - 255 LOW LUMINANCE 1. MODE: AGC / OFF 2. BRIGHTNESS: X0.25 - X1.00 MANUAL: 1. MODE: SHUT+AGC 3. AGC: 6.00 - 44.80 2. SHUTTER: 1/50 - 1/10000
WHITE BAL	ATW / PUSH / USER1 / USER2 / ANTI CR / MANUAL / PUSH LOCK ATW: 1. SPEED: 0 - 255 3. ATW FRAME: X0.50 - X2.00 2. DISPLAY CNT: 0- 255 4. ENVIRONMENT: INDOOR / OUTDOOR USER1: USER1 WB 1. B-GAIN: 0 - 255 2. R-GAIN: 0 - 255 USER2: USER2 WB 1. B-GAIN: 0 - 255 2. R-GAIN: 0 - 255 MANUAL: 1. LEVEL: 0-255
BACKLIGHT	OFF / BLC / HLC
PICT ADJUST	1. MIRROR: ON / OFF 5: HUE: 0 - 255 2. BRIGHTNESS: 0 - 255 6: GAIN: 0 - 255 3. CONTRAST: 0 - 255 7: DEFOG: OFF / LOW / MID / HIGH 4. SHARPNESS: 0 - 255
DWDR	ON / OFF ON: 1. LUMINANCE: LOW / MID / HIGH 2. CONTRAST: LOW / MID LOW / MID / MID HIGH / HIGH
MOTION DET	ON / OFF ON: 1. DETECT SENSE: 0 - 127 3. MOTION AREA: ON / OFF 2. BLOCK DISP: ON / OFF / ENABLE 4. AREA SEL: ENABLE: SET EXCLUSION AREA, TOP: 0 - 288 LONG PRESS TO SAVE AND EXIT BOTTOM: 0 - 288 LEFT: 0 - 468 RIGHT: 0 - 468
NEXT	DISPLAY MENU PAGE 2
SAVE ALL	SAVE ALL CURRENT SETTINGS
EXIT	EXIT MENU

Features

- Vandalproof Dome with 24 IR LEDs
- 700TVL
- 1/3" Sony Effio-E
- 3.6mm Megapixel board lens
- Up the Co-ax OSD control

Specification

FUNCTION	SPECIFICATION
CCD	1/3" Sony Effio-E
Resolution	700TVL - 752(H) x 582(V)
Lens	3.6mm Board /F2.0
IRs	24 x IRs up to 20m range
IR Power On	CDS auto control
Video Output	1v p ~ p, 75Ω
Video Connection	BNC
Power/Current	12vDC (± 10%) 275mA
Power Connection	2.1mm DC Socket
Auto Shutter	PAL: 1/50s ~ 1/100,00s
S/N Ratio	More than 48dB
Weatherproof	IP66
Operating Temp.	-10°C ~ +50°C
Dimensions	94mm(D) x 69mm(H)
Weight	400gms

Options Available

PART CODE	DESCRIPTION
CAM080UG	700TVL Eyeball, Grey
CAM080US	700TVL Eyeball, Silver
CAM080UW	700TVL Eyeball, White

Other Products To Consider



2.8-12mm Varifocal
700TVL IR Dome
Camera With WDR
& UTC. Available In
Grey, Silver & White
CAM083U



Up The Co-ax In-line
Controller
REM088

All specifications are approximate. System Q Ltd reserves the right to change any product specifications or features without notice. Whilst every effort is made to ensure that these instructions are complete and accurate, System Q Ltd cannot be held responsible in any way for any losses, no matter how they arise, from errors or omissions in these instructions, or the performance or non-performance of the equipment that these instructions refer to.

This symbol on the products and/or accompanying documents means that used electronic equipment must not be mixed with general household waste. For treatment, recovery and recycling please return this unit to your trade supplier or local designated collection point as defined by your local council.
WEE/CG0783SS

For more information on menu options and what they do see online tip 295 ▶▶▶



Menu Page 2

Menu Item	Options
PRIVACY	ON / OFF ON: 1. AREA SEL: 1/4 - 4/4 TOP: 0 - 288 BOTTOM: 0 - 288 LEFT: 0 - 468 RIGHT: 0 - 468 2. COLOUR: 1 - 8 3. TRANSP: 0.00 - 1.00 4. MOSAIC: ON / OFF
DAY/NIGHT	EXT1 / EXT2 / AUTO / COLOUR / B/W AUTO: 1. BURST: ON / OFF 2. DELAY CNT: 0 - 255 3. DAY→NIGHT: 0 - 255 4. NIGHT→DAY: 0 - 255 B/W: 1. BURST: ON / OFF 2. SMART IR: ON / OFF 3. MODE: AUTO / CENTRE 4. LEVEL: 0 - 31
DNR	1. NR MODE: Y/C / OFF / Y / C YC: Y LEVEL: 0 - 15 C LEVEL: 0 - 15 Y: Y LEVEL: 0 - 15 C: C LEVEL: 0 - 15
CAMERA ID	ON / OFF ON: SET CAMERA'S ID (NAME) AND THE POSITION OF THE ID ON-SCREEN
SYNC	INT
LANGUAGE	ENGLISH / JAPANESE / GERMAN / FRENCH / RUSSIAN / PORTUGUESE / SPANISH / CHINESE
CAMERA RESET	RESET CAMERA TO FACTORY DEFAULTS
COMMUNICATION	1. PROTOCOL: PELCO-D 2. ADDRESS: 0 - 254 3. BAUDRATE: 2.40 / 4.80 / 9.60 / 19.20 / 38.40 / 57.60 / 115.20
BACK	BACK TO MENU PAGE 1
SAVE ALL	SAVE ALL CURRENT SETTINGS
EXIT	EXIT MENU

Features

- Vandalproof Dome with 24 IR LEDs
- 700TVL
- 1/3" Sony Effio-E
- 3.6mm Megapixel board lens
- Up the Co-ax OSD control

Specification

FUNCTION	SPECIFICATION
CCD	1/3" Sony Effio-E
Resolution	700TVL - 752(H) x 582(V)
Lens	3.6mm Board /F2.0
IRs	24 x IRs up to 20m range
IR Power On	CDS auto control
Video Output	1v p ~ p, 75Ω
Video Connection	BNC
Power/Current	12vDC (± 10%) 275mA
Power Connection	2.1mm DC Socket
Auto Shutter	PAL: 1/50s ~ 1/100,00s
S/N Ratio	More than 48dB
Weatherproof	IP66
Operating Temp.	-10°C ~ +50°C
Dimensions	94mm(D) x 69mm(H)
Weight	400gms

Options Available

PART CODE	DESCRIPTION
CAM080UG	700TVL Eyeball, Grey
CAM080US	700TVL Eyeball, Silver
CAM080UW	700TVL Eyeball, White

Other Products To Consider



2.8-12mm Varifocal
700TVL IR Dome
Camera With WDR
& UTC. Available In
Grey, Silver & White
CAM083U



Up The Co-ax In-line
Controller
REM088

For more information on menu options and what they do see online tip 295 ▶▶▶



All specifications are approximate. System Q Ltd reserves the right to change any product specifications or features without notice. Whilst every effort is made to ensure that these instructions are complete and accurate, System Q Ltd cannot be held responsible in any way for any losses, no matter how they arise, from errors or omissions in these instructions, or the performance or non-performance of the equipment that these instructions refer to.

This symbol on the products and/or accompanying documents means that used electronic equipment must not be mixed with general household waste. For treatment, recovery and recycling please return this unit to your trade supplier or local designated collection point as defined by your local council.
WEE/CG0783SS

Fault Finding

The table below describes common problems and possible solutions.

Fault	Possible Cause	Possible Solution
Interference On The Camera Picture	Poor or inadequate cabling or an unregulated or poorly regulated power supply.	Make sure you are using a regulated 12V DC power supply.
No Picture	The camera cannot function without the correct working power supply.	<p>Step 1 Test that the camera has the correct voltage supplying it, you must do this with the camera connected so that there is load on the PSU. The camera should have at least 10.5V DC connected to it.</p> <p>Step 2 Check there is and image at the camera end with a test monitor. If there is a picture here but not at the DVR it could be one of the following:</p> <p>A. Video loss in Composite cable as run too long usually you would get a picture up to around 120mtrs (Remedied by fitting a video amp).</p> <p>B. Ensure that the BNC - BNC lead that you connect between the camera and monitor has no shorts or open circuits. If you are making your own lead, don't forget the lead must have two wires connected to complete the circuit, Video and Ground.</p> <p>C. No Video signal down CAT5 or CAT5+2. Check you have used a "pair of cores" not individual cores from different pairs.</p>
One Camera Picture Overlaid On Another Using CAT5	Camera cores and pairs mixed up.	Check you have used a "pair of cores" not individual cores from different pairs.
The Picture's Colour Changes Constantly	Fluorescent lighting emits an electromagnetic field which can cause colour roll.	Move the camera further away from any fluorescent lighting.

Features

- Vandalproof Dome with 24 IR LEDs
- 700TVL
- 1/3" Sony Effio-E
- 3.6mm Megapixel board lens
- Up the Co-ax OSD control

Specification

FUNCTION	SPECIFICATION
CCD	1/3" Sony Effio-E
Resolution	700TVL - 752(H) x 582(V)
Lens	3.6mm Board /F2.0
IRs	24 x IRs up to 20m range
IR Power On	CDS auto control
Video Output	1v p ~ p, 75Ω
Video Connection	BNC
Power/Current	12vDC (± 10%) 275mA
Power Connection	2.1mm DC Socket
Auto Shutter	PAL: 1/50s ~ 1/100,00s
S/N Ratio	More than 48dB
Weatherproof	IP66
Operating Temp.	-10°C ~ +50°C
Dimensions	94mm(D) x 69mm(H)
Weight	400gms

Options Available

PART CODE	DESCRIPTION
CAM080UG	700TVL Eyeball, Grey
CAM080US	700TVL Eyeball, Silver
CAM080UW	700TVL Eyeball, White

Other Products To Consider



2.8-12mm Varifocal
700TVL IR Dome
Camera With WDR
& UTC. Available In
Grey, Silver & White
CAM083U



Up The Co-ax In-line
Controller
REM088

All specifications are approximate. System Q Ltd reserves the right to change any product specifications or features without notice. Whilst every effort is made to ensure that these instructions are complete and accurate, System Q Ltd cannot be held responsible in any way for any losses, no matter how they arise, from errors or omissions in these instructions, or the performance or non-performance of the equipment that these instructions refer to.

This symbol on the products and/or accompanying documents means that used electronic equipment must not be mixed with general household waste. For treatment, recovery and recycling please return this unit to your trade supplier or local designated collection point as defined by your local council.
WEE/CG0783SS



For more information on menu options and what they do see online tip 295 ▶▶▶