

Features

- 32 x Video BNC Outputs
- 16 x Video BNC Inputs
- 12v DC 370mA
- (Free 1A psu supplied)
- Power LED
- 2U Rack Mount



1:2 Duplication

This video distribution amplifier allows for 16 video inputs and provides two outputs for each input. Typical use would be to provide sixteen video outputs to a 16 channel DVR and up to sixteen monitors displaying different full screen displays.

CCT157	Technical Specifications
Video Input Channel	16 Channels BNC
Video Output Channels	32 Channels BNC
Video Input Level	1V p-p 75 ohms
Video Output Level	1V p-p 75 ohms
Video Bandwidth	10Hz – 15MHz
Power Supply	12V DC
Power Connection	2.1 DC Jack
Power Consumption	370mA
Dimensions (mm)	482(w) x 105(d) x 90(h) mm
Fitting	2U Rack Mount

Troubleshooting

No Video Signal

1. Check power LED is lit. If not check power supply.
2. If connecting equipment such as Quads or DVRs these may reduce signal strength.
3. Avoid transmission distances in excess of 50 metres which may cause video signal degradation.



WEE/CG0783SS

This symbol on the products and/or accompanying documents means that used electronic equipment must not be mixed with general household waste. For treatment, recovery and recycling please return this unit to your trade supplier or local designated collection point as defined by your local council.

All specifications are approximate. Antihum.com reserves the right to change any product specifications or features without notice. Whilst every effort is made to ensure that these instructions are complete and accurate, Antihum.com cannot be held responsible in any way for any losses, no matter how they arise, from errors or omissions in these instructions, or the performance or non-performance of the equipment that these instructions refer to.